

Spin-on Line Filters



How to order

SP	-	06	-
Series	Omit of a set of filter, "H" is filter head, X is element	Nom. Dia. 0.6: RC3/4	Filtration mesh: 10mm, 25mm Omit : only buy filter head

Specification

Model	Max.press. (MPa)	Blow up press. (MPa)	By-pass valve setting (MPa)	Max.flow (L/min)	Filtr (μm)	Weight (kg)	Serew	Model of filter head	Model of element
SP-06 x 10	0.7	2.0	0.25	60	10	0.76	R3/4	SPH-06	SPX-06 x 10
SP-06 x 25				70	25	0.76	R3/4		SPX-06 x 25
SP-08 x 10				60	10	0.76	R1	SPH-08	SPX-08 x 10
SP-08 x 25				70	25	0.76	R1		SPX-08 x 25
SP-10 x 10				144	10	1.88	R1 1/4	SPH-10	SPX-10 x 10
SP-10 x 25				160	25	1.88	R1 1/4		SPX-10 x 25
SPA-10 x 10				200	10	2.70	R1 1/4		SPAX-10 x 10

Symbol

